


ARIK 6

design: Roberto Mantovani




Supply current
 Courant d'alimentation
 Corriente de alimentación
500mA (V_f 8.7V) (CC)

Power
 Pouissance
 Potencia
4.5W



FLEXALIGHTING
 NORTH AMERICA

Photometric diagrams



CCT	Flux	CRI	CCT	Flux	CRI
2400K	472 lm	95+	Dim to Warm	416 lm	90
2700K	421 lm	98+	1800K-3000K		
3000K	446 lm	98+			
3500K	464 lm	98+			
4000K	482 lm	98+			



Code Construction

Construction du code produit
 Construcción del código de producto

AW 6 X X XX CC E


AW	6	X	Finishing	X	Beam angle	XX	Color Temp.	CC	E
			Finitions Acabados		Angle de faisceau Ángulo del haz		Température couleur Temperatura de color		
			1 White Blanc Blanco		1 25°		24 2400K		
			5 Black Noir Negro		2 45°		27 2700K		
			C Custom Personnalisée Personalizado				30 3000K		
							35 3500K		
							40 4000K		
							DW Dim Warm		
							CU Custom Personnalisée Personalizado		

Drivers (Remote)

Alimentateurs
 Alimentadores

Series wiring

Câblage en série
 Cableado en serie



For other driver options -
 including Lutron, Dali and DMX -
 please consult factory

Static White	Phase / 0-10V (Dual Dimming)
500mA	CCPR010-A Min. 1 Max. 2
	CCPR040-A Min. 1 Max. 6
Dim to Warm	Phase / 0-10V (Dual Dimming)
250mA	CCPR010-A Min. 1 Max. 2
	CCPR040-A Min. 1 Max. 3

Optionals - Accessoires - Accesorios

DCVI.B.1

24VDC Constant Voltage to
 Constant Current Converter
 0-10V / Phase / Dim to Warm
 Compatible, 13W

