


BRAD

design: Lapo Grassellini




Supply current
 Courant d'alimentation
 Corriente de alimentación
350mA (V_f 14V)

Power
 Pouissance
 Potencia
5W



Photometric diagrams



CCT	Flux	CRI
3000K	250 lm	93
4000K	285 lm	93



Code Construction

Construction du code produit
 Construcción del código de producto

BD1 XX X


BD1	XX	Color Temp.	X	Finishing
		Température couleur Temperatura de color		Finitions Acabados
	30	3000K	B	White Blanc Blanco
	40	4000K	N	Black Noir Negro
	CU	Custom Personnalisée Personalizado	K	COR-TEN
			C	Custom Personnalisée Personalizado

Drivers (Remote)

Alimentateurs
 Alimentadores

Series wiring

Câblage en série
 Cableado en serie



For other driver options -
 including Lutron, Dali and DMX -
 please consult factory

Static White	Phase / 0-10V (Dual Dimming)	
350mA	CCPR010-A Min. 1 Max. 2	CCPR040-A Min. 1 Max. 4

Optionals - Accessoires - Accesorios

DCVI.B.1

24VDC Constant Voltage to
 Constant Current Converter
 0-10V / Phase / Dim to Warm
 Compatible, 13W

